


Telefon se konfiguruje přes www rozhraní. Po zapojení do sítě a propojení s PC nastavte do telefonu **IP adresu** (viz: Zkrácený návod). Tuto **IP adresu** zadejte do www prohlížeče na počítači připojeném ethernetem k telefonu.



Budete vyzváni k zadání přihlašovacích údajů. Uživatelské jméno a heslo nechte nevyplněno.

Registrar Server a Outbound Proxy: zjistíte na <http://www.802.cz/zjisteni-sip-serveru/>

SIP Phone Setting	
SIP Phone Port Number	5060
Registrar Server	
Registrar Server Domain Name/IP Address	Podle vašeho TO
Registrar Server Port Number	5060
Authentication Expire Time	600 sec. (Default: 3600 sec.)
Outbound Proxy Server	
Outbound Proxy Domain Name/IP Address	
Outbound Proxy Port Number	5060
Others	
Session Timer	1800 sec.
Media Port	41000
Prack	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
Session Refresher	<input checked="" type="radio"/> None <input type="radio"/> UAC <input type="radio"/> UAS
Session Timer Method	<input checked="" type="radio"/> Invite <input type="radio"/> Update
<input type="button" value="Submit"/> <input type="button" value="Reset"/>	

SIP Account Setting	
Default Account	Account 1
Account 1 Setting	
Account Active	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
Display Name	Vaše jméno
SIP User Name	Vaše telefonní číslo
Authentication User Name	Vaše telefonní číslo
Authentication Password	Vaše 802.cz heslo
Register Status	Register

Voice Setting	
Codec (Priority 1)	G.711 A-law
Codec (Priority 2)	G.729A
Codec (Priority 3)	G.723.1
Codec (Priority 4)	G.711 u-law
RTP Packet Length	G.711 μ -Law 20ms
	G.711 A-Law 20ms
	G.729A 20ms
	G.723.1 30ms
VAD	<input type="radio"/> On <input checked="" type="radio"/> Off
DTMF Method	<input type="radio"/> Out Band <input checked="" type="radio"/> In Band <input type="radio"/> SIP INFO
QoS	
Voice TOS	5 [0 - 7]
Warning: Enable/Disable WLAN might Caused Network Connection Problem!	
VLAN	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
<input type="button" value="Submit"/> <input type="button" value="Reset"/>	

Phone Setting	
Tone Setting	Germany
Ringer Type	RingType 4
Hold Tone	<input checked="" type="radio"/> Melody <input type="radio"/> Tone
Do Not Disturb	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
Call Waiting	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
Anonymous Call	<input checked="" type="radio"/> Disable <input type="radio"/> Full URI <input type="radio"/> Display Name
Anonymous Call Reject	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
Call Forward	<input type="checkbox"/> No Answer
	<input type="checkbox"/> Busy
	<input type="checkbox"/> Unconditional
Timer	
NTP Recycle Timer	1 hour [1 - 24] Network Time Adjustment Period
Inter Digit Timer	5 sec. [0 - 60] 0: Disable
Originating Not Accept Timer	0 sec. [0 - 600] 0: Disable
Incoming No Answer Timer	0 sec. [0 - 600] 0: Disable
Hold Recall Timer	180 sec. [0 - 600] 0: Disable
Auto Speaker Off Timer	30 sec. [0 - 600] 0: Disable
<input type="button" value="Submit"/> <input type="button" value="Reset"/>	